


In the box



Cloud Connector




Mounting bracket with adhesive backing




Power supply + regional plugs Cabel length: 2.5 m / 8.2 feet




Safety & Use leaflet with installation instructions



Drop ceiling bracket + screws and nuts



Wall screws + wall plugs



Ethernet cable

(Included with the Ethernet Only version of the Cloud Connector)

Installation Guidelines

Connecting to power


Use the provided power supply to power the Cloud Connector.

2 Connecting to the Cloud

If the device has a cellular modem, it will automatically start connecting to the cloud service. If not, plug in an ethernet cable to establish a connection.

3 Observe the Status Indicator

- Pulsing White
- Connecting / updating, this can take up to a few minutes.
- Solid White
- Connected to the internet and fully operational.
- Solid Red
 Not connected, visit <u>d21s.com/help</u> for troubleshooting.



Installation Guidelines

Wall or Ceiling Installation




Secure the mounting bracket to the wall with screws.

If mounted below 2 meters (6.5 feet), the adhesive can be used alone.





The Cloud Connector attaches to the bracket with a friction bayonet mount.




Align the slots and move the Cloud Connector onto the bracket.



Turn the Cloud Connector 45° degrees to secure it in place and connect the power cable.

Drop Ceiling Installation



Remove the tile from the ceiling to perform the installation.

The mounting bracket is attached to the tile using the provided backing plate with two screws and nuts.

The Cloud Connector attaches to the bracket with a friction bayonet mount.

